

## Boolean Algebra

**Definition:** A two-valued Boolean algebra is defined on a set of 2 elements  $B = \{0,1\}$  with 3 binary operators OR (+), AND ( $\bullet$ ), and NOT ( $'$ ).

		B	
	+	0	1
0	0	0	1
1	1	1	1

		B	
	$\bullet$	0	1
0	0	0	0
1	1	0	1

	'		
0		1	
1		0	

### 3.2 Axioms - need no proof.

1. Closure Property.  
The result of each operation is an element of  $B$ .
2. Identity Element.
  - a) 1 for AND because  $x \bullet 1 = 1 \bullet x = x$ .
  - b) 0 for OR because  $x + 0 = 0 + x = x$ .
3. Commutative Property. From the symmetry of the tables.
  - a)  $x \bullet y = y \bullet x$ .
  - b)  $x + y = y + x$ .
4. Distributive Property.
  - a)  $x \bullet (y + z) = (x \bullet y) + (x \bullet z)$ .
  - b)  $x + (y \bullet z) = (x + y) \bullet (x + z)$ .

To show that this is true, we need to show that for any value of binary variables  $x$ ,  $y$ , and  $z$ ,  $x \bullet (y + z)$  will have the same value as  $(x \bullet y) + (x \bullet z)$ .

$x$	$y$	$z$	$y+z$	$x(y+z)$	$xy$	$xz$	$(xy) + (xz)$
0	0	0	0	<b>0</b>	0	0	<b>0</b>
0	0	1	1	<b>0</b>	0	0	<b>0</b>
0	1	0	1	<b>0</b>	0	0	<b>0</b>
0	1	1	1	<b>0</b>	0	0	<b>0</b>
1	0	0	0	<b>0</b>	0	0	<b>0</b>
1	0	1	1	<b>1</b>	0	1	<b>1</b>
1	1	0	1	<b>1</b>	1	0	<b>1</b>
1	1	1	1	<b>1</b>	1	1	<b>1</b>

5. Complement Element. For every  $x \in B$ , there exists a complement element  $x' \in B$  such that:
  - a)  $x + x' = 1$        $0 + 0' = 0 + 1 = 1$  and  $1 + 1' = 1 + 0 = 1$
  - b)  $x \bullet x' = 0$        $0 \bullet 0' = 0 \bullet 1 = 0$  and  $1 \bullet 1' = 1 \bullet 0 = 0$
6. Cardinality Bound. There are at least 2 elements  $x, y \in B$  such that  $x \neq y$ .  $0 \neq 1$ .

**3.3 Basic Theorems** - need to be proven.

1. Idempotency.
  - a)  $x + x = x$ .
  - b)  $x \bullet x = x$ .
2. a)  $x + 1 = 1$ .  
b)  $x \bullet 0 = 0$ .
3. Absorption.
  - a)  $yx + x = x$
  - b)  $(y + x)x = x$
4. Involution.
  - a)  $(x')' = x$
5. Associative.
  - a)  $(x + y) + z = x + (y + z)$
  - b)  $x (y z) = (x y) z$

**Proof of 1a)**  
 $x + x = (x + x) \bullet 1$  by Axiom 2a  
 $= (x + x) (x + x')$  by Axiom 5a  
 $= x + xx'$  by Axiom 4b  
 $= x + 0$  by Axiom 5b  
 $= x$  by Axiom 2b

**Proof of 3a)**  
 $yx + x = yx + 1x$  by Axiom 2a  
 $= x(y + 1)$  by Axiom 4a  
 $= x1$  by Theorem 2a  
 $= x$  by Axiom 2a

**Proof of 3b)**  
 $(y + x)x = xy + xx$  by Axiom 4a  
 $= xy + x$  by Theorem 1b  
 $= x$  by Theorem 3a

**Proof of 3b)**

$x$	$y$	$y+x$	$(y+x)x$
0	0	0	0
0	1	1	0
1	0	1	1
1	1	1	1

**De Morgan's Law.**

- a)  $(x + y)' = x' y'$
- b)  $(x y)' = x' + y'$


**Duality Principle.**

This principle states that any algebraic equality derived from these axioms will still be valid whenever the OR and AND operators, and identity elements 0 and 1, have been interchanged. i.e. changing every OR into AND and vice versa, and every 0 into 1 and vice versa.

Ex. Theorem 1b) follows from Theorem 1a) by the duality principle.

**3.4 Boolean Functions**

Boolean functions are formed from binary variables and the Boolean operators AND, OR, and NOT. For a given value of the variables, the value of the function is either 0 or 1. e.g.



This function equals 1 if:

- $x = 1$  and  $y = 1$  (doesn't matter what  $z$  is)
- $x = 1, y = 0,$  and  $z = 1$
- $x = 0, y = 1,$  and  $z = 1$

otherwise,  $F_1 = 0$ .

Boolean functions can also be defined by a truth table:

Variable Values			Function Values	
$x$	$y$	$z$	$F_1$	$F_1'$
0	0	0	0	1
0	0	1	0	1
0	1	0	0	1
0	1	1	1	0
1	0	0	0	1
1	0	1	1	0
1	1	0	1	0
1	1	1	1	0

$$\begin{aligned}
 x y z + x y z' &= x y (z + z') \\
 &= x y (1) \\
 &= x y
 \end{aligned}$$

### 3.4.1 Complement of a Function

The complement of any function  $F$  is  $F'$ . Its value can be obtained by interchanging the 0's for 1's and 1's for 0's in the value of  $F$ .

There are two ways to determine the algebraic expression for the complement of a function:

1. Apply the generalized form of De Morgan's Law as many times as necessary.

$$\begin{aligned}
 \text{Ex. } F' &= (x y + x y' z + x' y z)' \\
 &= (x y)' (x y' z)' (x' y z)' \\
 &= (x' + y') (x' + y + z) (x + y' + z')
 \end{aligned}$$

Difficult to see when  $F' = 1$ . Easier to see when  $F' = 0$ .  $F' = 0$  when each term is 0.

2. Use the duality principle, i.e. interchange the AND and OR operators, and by complementing each literal.

$$\begin{aligned}
 \text{Ex. } (x y) &\Rightarrow (x' + y') \\
 (x y' z) &\Rightarrow (x' + y + z') \\
 (x' y z) &\Rightarrow (x + y' + z') \\
 \text{therefore, } (x y) + (x y' z) + (x' y z) &\Rightarrow (x' + y') (x' + y + z') (x + y' + z')
 \end{aligned}$$

The same function can be specified by two or more different algebraic expressions.

### 3.4.2 Graphic representation

Boolean functions can be expressed graphically by connecting together AND, OR, and NOT operators, as specified by the algebraic expression that was used to define the function.

$$\text{Ex. } F_1 = (x y) + (x y' z) + (x' y z)$$

